

Connecting an Idesco Access 8 CD reader to Net2

Overview

The CD designation allows the reader to work with Mifare DESfire tokens.


The card tested was configured to provide a 26 bit Wiegand output.

To set up a Wiegand filter to screen out the card number, you will need to use the Net2 Server configuration utility. Once completed, select the reader 'Token data format' in Net2 to 'Wiegand Custom'.

See:
AN1010 - Configuring custom Wiegand formats < <http://paxton.info/990> >
for more information



Cable Pinout	ACU terminal
Red	+12V
Brown	Red LED
-	Amber LED
Blue	Green LED
Green	Wiegand D0
White	Wiegand D1
-	NOT USED
Black	0V



Ensure any unused wires are safely terminated.


To configure the LED setting, open the Net2 server configuration utility and on the 'General' tab, check the 'Display reader LED's in OEM style' box.

If the option is not available, please contact Technical support for further advice.

 +44 (0)1273 811011
support@paxton.co.uk
paxton.support


 +49 (0) 251 2080 6900
support@paxton-gmbh.de
paxton.gmbh.support


 +33 (0)157 329356
support@paxtonaccess.fr
paxton.support


 +32 (0)78485147
support@paxton-benelux.com
paxton.benelux.support


 +31 (0)76 3333 999
support@paxton-benelux.com
paxton.benelux.support

 +27 (0)21 4276691
support@paxtonaccess.co.za
paxton.support

 +1(800) 672-7298
supportUS@paxton-access.com
usapaxton.support

 +11 5715088198
soporte@paxton-access.com
paxton.soporte

 +1 (864) 751-3501
soporte@paxton-access.com
paxton.soporte

 8000 3570 3783
support@paxtonaccess.ae
paxton.support

 +44 (0)1273 811011
support@paxton.co.uk
paxton.support