


Technical Support

 01273 811011

 support@paxton.co.uk

Technical help is available: Monday - Friday from 07:00 - 19:00 (GMT)
Saturday from 09:00 - 13:00 (GMT)

Documentation on all Paxton products can be found on our website - <http://www.paxton.co.uk/>

Desktop Reader

The desktop reader is designed to sit next to the PC. It is used for adding tokens to a Net2 system and also for identifying lost cards. Additional workstations can also have desktop readers.

With the Net2 software running, any new token presented above the desktop reader will cause the new user wizard to appear with the card number displayed. Additional user details can then be entered.

If the token is already known to the system, the relevant users' record will appear.



The reader will accept:

- Paxton tokens
- Paxton hands free tokens (passive mode)
- Mifare® Classic protocol (ISO 14443A)
- Mifare® Ultralight /C
- Mifare® Desfire
- EM4100 tokens
- Hitag 1 tokens

Installation

Download the latest version of Net2 software at: <http://paxton.info/1438> before commissioning this product.

The power for the unit is supplied via the USB cable. No additional power supply is required.

Plug the reader into a convenient USB port on the PC using the supplied USB cable.

Stop and then restart the Net2 server program. The device will now be available to the Net2 program.


Specifications			
Environment	Min	Max	
Operating temperature	0 °C	+55 °C	
Waterproof			No
Electrical	Min	Max	
Voltage	4.75V DC	5.25V DC	USB certified
Current		100 mA	
Dimensions	Width	Depth	Height
	115 mm	75 mm	19 mm

CE0889

The declaration of conformity is available on request. Contact details are provided at: <http://paxton.info/596>

This product is not suitable for retail sale. All warranties are invalid if this product is not installed by a competent person.

Technical Support

 01273 811011

 support@paxton.co.uk

Technical help is available: Monday - Friday from 07:00 - 19:00 (GMT)
Saturday from 09:00 - 13:00 (GMT)

Documentation on all Paxton products can be found on our website - <http://www.paxton.co.uk/>

Desktop Reader

The desktop reader is designed to sit next to the PC. It is used for adding tokens to a Net2 system and also for identifying lost cards. Additional workstations can also have desktop readers.

With the Net2 software running, any new token presented above the desktop reader will cause the new user wizard to appear with the card number displayed. Additional user details can then be entered.

If the token is already known to the system, the relevant users' record will appear.



The reader will accept:

Paxton tokens
Paxton hands free tokens (passive mode)

Mifare® Classic protocol (ISO 14443A)
Mifare® Ultralight /C
Mifare® Desfire

EM4100 tokens
Hitag 1 tokens

Installation

Download the latest version of Net2 software at: <http://paxton.info/1438> before commissioning this product.

The power for the unit is supplied via the USB cable. No additional power supply is required.

Plug the reader into a convenient USB port on the PC using the supplied USB cable.

Stop and then restart the Net2 server program. The device will now be available to the Net2 program.

Specifications			
Environment	Min	Max	
Operating temperature	0 °C	+55 °C	
Waterproof			No
Electrical	Min	Max	
Voltage	4.75V DC	5.25V DC	USB certified
Current		100 mA	
Dimensions	Width	Depth	Height
	115 mm	75 mm	19 mm

CE0889

The declaration of conformity is available on request. Contact details are provided at: <http://paxton.info/596>

This product is not suitable for retail sale. All warranties are invalid if this product is not installed by a competent person.